

PCMCIA Serial Card Adapter CE Model 232PCC

B&B Electronics' **232PCC** adds a high-speed serial port to any product that has a Type II or III PCMCIA interface. The 232PCC is compatible with all PC software and connects to all standard serial peripherals.



Specifications:

PCMCIA Type II (85.6 x 54.0 x 5 mm)
Long interconnect cable
RS-232 9-pin serial connector

The **232PCC** has a **16550 UART** allowing Microsoft Window users to run the new generation modems and other serial peripherals at full speed.

Power Consumption:

25 mA - Active
5 mA - Non-active

DOS COM ports 1 - 4 compatibility
FCC Part 15, Class B Compliance

Popular devices that can be interfaced to the 232PCC through Type II PCMCIA slots are:

Fax/Modems
Serial Mouse
Test Equipment
Printers
Scanners

All equipment requiring a serial connection

Programmable Characteristics:

Character length: 5-, 6-, 7- or 8-bit
Parity: Even, odd or none
Baud rate: Up to 115.2k

Software Included:

PCMCIA Interface Software (Point Enabler)

Features:

- 232PCC works with Type II, III or Toshiba Type IV PCMCIA slots
- Based on internally-buffered 16550 UART chip for maximum data throughput
- Includes standard RS-232 (9-pin) connector
- Supports popular PCMCIA controllers
- Windows 95 and 98 drivers included
- Includes installation software that is easy and quick to install
- Can run memory or I/O mapped, interrupt driven or polled - adaptable to any PCMCIA compatible host
- Low power (25mA) for compatibility with PDA's
- Three energy conservation modes
- Can run as COM 1, 2, 3 or 4 under DOS
- Software configurable

DECLARATION OF CONFORMITY

Importer's Name:	B&B Electronics Manufacturing Company
Importer's Address:	P.O. Box 1040 707 Dayton Road Ottawa, IL 61350 USA
Model Numbers:	232PCC
Description:	PCMCIA High-Speed Serial Card
Type:	Light industrial ITE equipment
Application of Council Directive:	89/336/EEC
Standards:	EN 50082-1 (IEC 801-2, IEC 801-3, IEC 801-4) EN 50081-1 (EN 55022) EN 61000 (-4-3, -4-4) ENV 50204

Michael J. Fahrion, Director of Engineering

B&B Electronics -- Revised January 1999

This product designed and manufactured in USA of domestic and imported parts by

B & B Electronics Mfg. Co.

707 Dayton Road - P.O. Box 1040 - Ottawa, IL 61350 USA
Phone: (815) 433-5100 - Fax: (815) 433-5105

Home Page: www.bb-elec.com

Sales e-mail: orders@bb-elec.com - Fax: (815) 433-5109
Technical Support e-mail: support@bb-elec.com - Fax: (815) 433-5104

B & B Electronics Ltd

Westlink Commercial Park - Oranmore, Co. Galway - Ireland
Phone: +353 91 792444 - Fax: +353 91 792445

Home Page: www.bb-europe.com

Sales e-mail: orders@bb-europe.com
Technical Support e-mail: support@bb-europe.com